

## i-GATE

GSM gate opener with IOS & Android Apps.

Numbers for caller ID access.

FOTA – Upgrade firmware via SMS.

Trigger, latch and unlatch gates by SMS or with app.

Auto call feature to schedule outgoing call (prevents SIM card being deactivated).

Activity log feature.

Includes 7 day time clock.

Check stored numbers by SMS.

Volt free momentary relay outputs.

Check if gates are opened or closed.

Check relay status.

SMS passcode access for non stored numbers.

Store up to four phone numbers to receive SMS alerts each time the unit is used to grant access.

Program times for the relay(s) to operate automatically.

E-LOOP\* Connection Features.

SMS Notification when E-loop battery is low (4 Numbers).


Push-To-Exit time limits & suspend times.

E-Loop only OR E-Loop & remote lock out times.

Program E-loop, 7 day time clock, automatic gate opening and close times etc.

Area code:  
EU (Europe)  
US (USA)  
AU (Australia & NZ)

\*e-Loop sold separately.  
\* Full app functionality will be released at a later date. Direct SMS commands can be used.



### I-GATE-PRIME



### I-GATE-1200



### I-GATE-PLUS



250

1200

1200



2

1

1



### DETAILS

|                |                                     |
|----------------|-------------------------------------|
| Power          | 12-24v ac/dc (not supplied)         |
| Current        | 45mA (standby). 200mA (when called) |
| Weather Rating | IP67                                |
| Relay Load     | 24v 2A                              |
| Relay Type     | N/C and N/O. Latching & momentary   |